

iGL-RA15 Remote annunciator

Remote (CAN bus, up 200 meters) 15 LED states indicator. One iGL-RA15 unit can be connected to iG-CUa via CAN as Binary output address 13 and 14. Detail descriptions see in iGL-RA15.pdf user guide.

